

Pre-Conditions

- The distributor has received a LAC; for this example 420004502_1
- The reseller received this LAC
- The reseller has an account on the CLS
- The reseller has signed to contracts with the end customer; the tenantID is known to the reseller; for this example: 050467381626. The tenant's company will be *NewCO Inc*
- The reseller in this example is called *Unify*

Process Steps

- Open a browser and connect to <https://www.central-license-server.com>. Insert credentials to **Log In**

UNIFY Harmonize your enterprise

View in another language Eng

Welcome to the Central License Server

Welcome to the Central License Server

Log in:

* Username:

* Password:

[Log In](#)

[Not registered? Login with a LAC, instead.](#)

Product Information

TeleData Office [Activation of Feature / Tariff Tables](#)

If you don't have a login

Contact the License Administrator within your company and request a login and password
If there is no License Administrator in your company, please contact the User Support

- The next page already asks for the LAC. Insert the LAC and press **Activate**

UNIFY Harmonize your enterprise

Logged in as: **Hanna Thomas**

Home Licenses Activation Calculate Locking ID Reports Administration Product Information Help

Home

Activate Your Software HERE:

- 1 Enter your LAC
- 2 Enter your machine information
- 3 Get your key

LAC: **Activate**

Welcome to CLS!
For your orientation there is our quick reference guide available via a red link below. You may also make use of our new help system available on the right hand side in the menu at the top. In addition there are green, encircled question marks on almost all pages below their title. These take you to a help specific to that page.
The introduction of the Machine concept has lead to new workflows for network licensing. The slides linked below describe the new workflows.

- Insert the reseller's company name and search via the magnifier button

Search Machines ?

Use this form to select the machine to use for the activation. You may also be able to add a new machine. The machine must belong to the registered company. You can search for machines using the machine name, a locking ID on the machine, or a SIEL-ID. To display additional criteria, click Advanced Search. [Click here for additional Search Tips](#)

%indicates wildcard search

%Company name:


%Machine name:

Locking ID:

SIEL-ID:

Search Machines **Cancel** [\[Advanced Search\]](#)

- Complete the search on the following screens and finally choose the correct company

Search Companies 

Use this page to search for and select the company you want to use. You can search for the company based on the name, ID, type, or status. To display additional criteria, click Advanced Search. After providing search criteria, to display a list of companies, click Search Companies. To select the company, click its Select link. [Click here for additional Search Tips](#)

%indicates wildcard search

%Name:

ID:

Type:

Status:


[\[Advanced Search\]](#) [\[Add a company\]](#)

Showing: 1-3 of 3

Select	ID	Name	Status	HQ Country	HQ City	Type
Select	0000-10032588	UNIFY	Active	Ireland	Dublin	Local Company
Select	0000-10034811	UNIFY	Active	Germany	Frankfurt	Local Company
Select	0000-10039967	UNIFY	Active	United States	San Jose	Local Company


Showing: 1-3 of 3

- As Circuit is not a real shipped item, the "machine" does not show up in the reseller's inventory, therefore select "Add a machine" to a new entry for the Circuit SBL.

Search Machines 

Use this form to select the machine to use for the activation. You may also be able to add a new machine. The machine must belong to the registered company. You can search for machines using the machine name, a locking ID on the machine, or a SIEL-ID. To display additional criteria, click Advanced Search. [Click here for additional Search Tips](#)

%indicates wildcard search

%Company name: 

%Machine name:

Locking ID:

SIEL-ID:

[\[Advanced Search\]](#) [\[Add a Machine\]](#)

- Provide an easy to remember name, you can identify easily later on, e.g. **Circuit for ENDCUSTOMER TenantID TENANTID**. Make sure not to have special characters like "." in the machine name. Press **Save**

to proceed.

Add Machine ?

Provide the name of the new machine, then click Save. If you can have the system generate a name for you, then a Suggest displays next to the field.

*Machine name:

Machine Group Identifier:
Machine Group Owner:

- Check, if the registration data is correct and proceed with **Next**

Activate Entitlements ?

Quick Keys **Register** Activate Confirm Complete

The company and user listed below are the registered company and user for this transaction.

Company data	User data
UNIFY - 0000-10034811 Lyoner Str.27 Frankfurt, 60528 Germany	

- Insert the TenantID in the Tenant ID field and proceed with **Next**

Activate Entitlements ?

Quick Keys Register **Activate** Confirm Complete

Please provide any required information. When you are finished, click Next.

CAUTION: For virtual systems the Advanced Locking ID has to be used. For hardware based systems the MAC address is of relevance. To calculate the Advanced Locking ID click the "Calculate Locking ID" link on Top Menu.

Machine Name	Machine Information
<input type="text" value="Circuit for NewCO Inc. TenantID 050467381626"/> * Tenant ID:	<input type="text" value="050467381626"/>

Quantity to Use	Available Quantity	Existing Quantity	New System	Entitlement
<input type="text" value="1"/>	1		0	Circuit Tenant Base Code Feature #:F31505-K231-A1;Product Version:V1.0;Product Language:All;Platform:All;License Type:License; <i>Status:Un-Assigned</i> ;Product Line:Circuit;Feature:Circuit Tenant Base Code;LAC:420004502_1;License Id:14238841

- Check mark the two check boxes. Please note, that the emails usually send out by CLS to the end customer's containing the SBL need to be enhanced in order to display the correct SBL. Therefore as an interim solution, the SBL has to manually be send to the end customer.

Press **Finish**.

Activate Entitlements

?

Quick Keys Register Activate **Confirm** Complete

Cancel < Back Finish

Legal Notice

Before you can complete this process, you must agree to the following notice.

As your company's registered user, you warrant that: UPON CHECKING THIS CHECKBOX YOU AGREE TO

I agree with the above terms.

Confirmation Information

From the Result output dropdown, select whether to email affected certificates, and, if you are emailing certificates, the format to use. To send certificates to specific email addresses, enter email addresses in the Email to field. Use commas to separate multiple addresses.

Do not email certificate to registered user

Result output: None

Email to: (Multiple separated by commas)

Language: English

Comments:

Notes for this transaction

You can add notes concerning this transaction.

Notes Internal Notes

Here is a summary of this activation transaction.

1 entitlement(s) will be activated on machine Circuit for NewCO Inc TenantID 050467381626 as a result of this transaction

Cancel < Back Finish

- Go to the "View Certificates" section of CLS and open **Keys** tab. Hit the "**Save to File**" link

View Certificate (Circuit for NewCO Inc TenantID 050467381626)

?

Return to previous page **Print** Options

Overview Ownership **Keys** Transactions

Below are the current keys associated with this machine.

Activated:	Aug 2, 2016
Product line:	Circuit

Circuit license key

Save to File

[View Activation Details](#)

- An html file will be generated that can be send to the end customer. The html contains the SBL.

CIRCUIT Activation Keys

Use the below activation keys for your CIRCUIT instances.

Activation Key	Issue Date
de8d8d28-e6c9-42ed-9; 618	2016-08-02 17:13:25.0

- The email send to the customer should provide a quick directive of what to do with the SBL,
- Please open a browser and navigate to <https://www.circuit.com/unifyportalshop>
- As circuit tenant administrator, please authenticate yourself with your Circuit username and password.
- Insert the Activation Key provided in this email when being asked for an "Entitlement Token"
- The Circuit eStore is now enabled for your self management. Please note that the Circuit eStore displays list prices that might differ from your contractual agreements with us.